



## SELF-CONTAINED DIGITAL ACCESS CONTROL KEYPADS For Residential and Commercial Applications

# DK-9562 • DK-9561 • DK-9560

**New Programming Software, New Construction, Fine Workmanship**

**DK-9562 2 Relay Outputs Full Feature System**

**DK-9561 1 Relay & 1 Transistor Output Full Feature System**

**DK-9560 1 Relay Output Compact System**

CE  
RoHS COMPLIANT



**DK-9562 / DK-9561**



**DK-9560**

### FEATURES AND FUNCTIONS:

- WIDE RANGE OPERATING VOLTAGE 12-24V AC/DC
- BACK-LIT KEYPAD
- OPERATE FAIL-SAFE OR FAIL-SECURE ELECTRIC LOCKS
- AUTO CODE ENTRY OR MANUAL CODE ENTRY
- DOOR FORCED OPEN WARNING
- DOOR LEFT OPEN TOO LONG WARNING
- OUTPUT ACTIVATION ANNOUNCER
- PACIFIER TONE ON-OFF OPTIONS
- KEYPAD LOCKS OR ALARMS AFTER 3-10 FALSE CODE ENTRIES
- SINGLE USER MODE OR MULTI-USER MODE
- KEY ACTIVATION, ALARM, TAMPER SWITCH OUTPUTS
- TAMPER BEEP FUNCTION WITH ON-OFF OPTION
- EGRESS INPUT FOR DOOR-OPEN REMOTE TRIGGERING
- FEATURES ARE KEYPAD PROGRAMMABLE
- NON-VOLATILE MEMORY IN POWER FAILURE
- STAINLESS STEEL PLATE
- FLUSH MOUNT OR SURFACE MOUNT

MANUFACTURER & EXPORTER




ADVANCED ELECTRONICS INDUSTRY LIMITED  
HONG KONG

TEL : (852) 24299719  
FAX : (852) 24892411  
E-MAIL : [aei@aei-secucom.com](mailto:aei@aei-secucom.com)  
WEBSITE : <http://www.aei-secucom.com>

## MULTI-PURPOSE SELF-CONTAINED DIGITAL ACCESS CONTROL KEYPAD

## DK-9562 - - 2 OUTPUTS: DUAL RELAY OUTPUT

DK-9562




### FEATURES AND FUNCTIONS:

- 500 User Codes
- Operates Fail-safe or Fail-secure Electric Locks
- Auto Code Entry or Manual Code Entry
- Door Forced Open Warning
- Door Left Open Too Long Warning
- Output Activation Announcer
- Pacifier Tone Inhibit Control, Audible or Silent Operation
- Keypad Locks or Alarms After 3-10 False Code Entries
- Tamper Beep Available or Tamper Beep Disabled
- Key Activation, Alarm, Tamper Outputs
- Egress Input for Door-open Remote Triggering
- Features are Keypad Programmable
- Non-volatile Memory in Power Failure
- Stainless Steel Plate
- Flush Mount or Surface Mount

**DK-9561 - - 2 OUTPUTS: 1 RELAY OUTPUT, 1 TRANSISTOR OPEN COLLECTOR OUTPUT**

DK-9561



**SPECIFICATIONS:**

**Operating Voltage:** 12-24V AC/DC

**Current Drain:** Quiescent State= 26-35 mA (DK-9562) 26-35 mA (DK-9561)  
Active State= 85-103 mA (DK-9562) 70-85 mA (DK-9561)

**Relay Output Contacts:** N.O. and N.C. Dry Contacts,  
Max Rating of Contact Current 3A/24V DC


**Capacity of Recording:** Output 1: 500 Codes  
Output 2: 500 Codes

**Dimension:** 117(H) mm x 74(W) mm x 48(D) mm

**Weight:** 165g (DK-9562) 160g (DK-9561)

### DK-9560 - - 1 OUTPUT: SINGLE RELAY OUTPUT

DK-9560



### FEATURES AND FUNCTIONS:

- Simple Programming, Easy Operation
- 250 User Codes
- Multi User Code or Single User Code Operation
- Operates Fail-safe or Fail-secure Electric Locks
- Auto Code Entry or Manual Code Entry
- Keypad Locks for 30 Seconds After 10 False Code Entries
- Tamper Beep Available or Tamper Beep Disabled
- Tamper Switch can be Connected to Security Alarm System
- Egress Input for Door-open Remote Triggering
- Features are Keypad Programmable
- Non-volatile Memory in Power Failure
- Stainless Steel Plate
- Flush Mount or Surface Mount

**SPECIFICATIONS:**

**Operating Voltage: 12-24V AC/DC**

**Current Drain:** Quiescent State=25-33mA  
Active State=61-79mA

**Relay Output Contacts:** N.O. and N.C. Dry Contacts,  
Max Rating of Contact Current 3A/24V DC

**Capacity of Recording:** 250 Codes or 1 Common Code

**Dimension:** 117(H) mm x 74(W) mm x 48(D) mm

**Weight: 158g**

### SUMMARY CHART

| PRODUCT \ FEATURE | OPERATING VOLTAGE | RELAY & TRANSISTOR OUTPUTS              | DOOR FORCED OPEN WARNING | DOOR LEFT OPEN TOO LONG WARNING | AUTO OR MANUAL CODE ENTRY | RELAY ACTIVATION ANNOUNCER | PACIFIER TONE (ON-OFF OPTIONS) | KEY ACTIVATION OUTPUT | DOOR AUTO RELOCK | ALARM OUTPUT | EGRESS BUTTON INPUT | TAMPER SWITCH | TAMPER BEEP FUNCTION (ON-OFF OPTION) | SINGLE/ MULTI-USER OPTIONS |
|-------------------|-------------------|-----------------------------------------|--------------------------|---------------------------------|---------------------------|----------------------------|--------------------------------|-----------------------|------------------|--------------|---------------------|---------------|--------------------------------------|----------------------------|
| DK-9562           | 12-24V AC/DC      | 2 RELAY OUTPUT                          | YES                      | YES                             | YES                       | YES                        | YES                            | YES                   | YES              | YES          | YES                 | YES           | YES                                  | YES                        |
| DK-9561           | 12-24V AC/DC      | 1 RELAY OUTPUT &<br>1 TRANSISTOR OUTPUT | YES                      | YES                             | YES                       | YES                        | YES                            | YES                   | YES              | YES          | YES                 | YES           | YES                                  | YES                        |
| DK-9560           | 12-24V AC/DC      | 1 RELAY OUTPUT                          | NO                       | NO                              | YES                       | NO                         | NO                             | NO                    | NO               | NO           | YES                 | YES           | YES                                  | YES                        |